

MARTIN

Massachusetts Institute of Technology
Instrumentation Laboratory
Cambridge, Massachusetts

Space Guidance Analysis Memo # 38-64

TO: SGA Distribution
FROM: Peter J. Philliou
DATE: September 23, 1964
SUBJECT: Optimal Guidance Laws

The material in this memo is taken primarily from lectures given by Professor Bryson. A general guidance law is presented and then it is applied to

- (a) injection
- (b) interception
- (c) rendezvous
- (d) soft landing

Let subscript p denote the pursuing body and T the target body.

The equations of motion are

$$\dot{\underline{v}}_T = \underline{f}_T$$

where \underline{f}_T = external forces per unit mass

$$\dot{\underline{v}}_p = \underline{f}_p + \underline{a}$$

where \underline{a} = control acceleration

$$\dot{\underline{r}}_T = \underline{v}_T$$

$$\dot{\underline{r}}_p = \underline{v}_p$$

We now have 12 equations, but we want relative values, consequently the 12 equations reduce to 6 by letting

$$\underline{v} = \underline{v}_p - \underline{v}_T$$

$$\underline{r} = \underline{r}_p - \underline{r}_T$$

$$\underline{f} = \underline{f}_p - \underline{f}_T$$

The 6 equations are

$$\begin{aligned} \dot{\underline{v}} &= \underline{f} + \underline{a} \\ \dot{\underline{r}} &= \underline{v} \end{aligned} \quad t_0 \leq t \leq t_1$$

where t_0 is initial time and t_1 is final time. The problem is to find the control law \underline{a} which minimizes the cost function J , where J is assumed to be

$$J = \frac{1}{2} \left[C_v \underline{v} \cdot \underline{v} + C_r \underline{r} \cdot \underline{r} \right]_{t_1} + \int_{t_0}^{t_1} \frac{a^2}{2} dt$$

and which satisfies the differential equations

$$\dot{\underline{v}} = \underline{f} + \underline{a}$$

$$\dot{\underline{r}} = \underline{v}$$

This is a control problem to minimize J , the cost function, with initial state, time and final time fixed. The cost function J considers fuel cost and C_r, C_v are weighting factor constants for position and velocity. Form the Hamiltonian

$$H = \frac{a^2}{2} + \underline{\lambda} \cdot \underline{v} + \underline{p} \cdot (\underline{f} + \underline{a})$$

and consider the Hamiltonian system (differential equations associated with H)

$$\dot{\underline{p}} = -\frac{\partial H}{\partial \underline{v}} = -\underline{\lambda}$$

$$\dot{\underline{\lambda}} = -\frac{\partial H}{\partial \underline{r}} = 0 \rightarrow \underline{\lambda} = \text{constant}$$

\underline{p} , $\underline{\lambda}$ are the adjoint free vectors.

For optimality (special case of maximum principle)

$$\frac{\partial H}{\partial \underline{a}} = 0 = \underline{a} + \underline{p} \rightarrow \underline{a} = -\underline{p}$$

$$\underline{p} = -(t - t_0) \underline{\lambda} + \underline{p}_0$$

solving for \underline{a}

$$\underline{a} = (t - t_0) \underline{\lambda} - \underline{p}_0 \quad (1)$$

$$\dot{\underline{v}} = \underline{f} + (t - t_0) \underline{\lambda} - \underline{p}_0$$

$$\dot{\underline{r}} = \underline{v}$$

from transversality conditions

$$\underline{p}(t_1) = C_v \underline{v}(t_1)$$

$$\underline{\lambda}(t_1) = C_r \underline{r}(t_1)$$

let

$$\underline{v}(t_0) = \underline{v}_0$$

$$\underline{r}(t_0) = \underline{r}_0$$

solve for \underline{v} , \underline{r} with $\underline{f} = \text{constant}$

$$\underline{v} = (t - t_0) \underline{f} + \frac{(t - t_0)^2}{2} \underline{\lambda} - \underline{p}_0 (t - t_0) + \underline{v}_0 \quad (2)$$

$$\underline{r} = \frac{(t - t_0)^2}{2} \underline{f} + \frac{(t - t_0)^3}{6} \underline{\lambda} - \underline{p}_0 \frac{(t - t_0)^2}{2} + \underline{v}_0 (t - t_0) + \underline{r}_0 \quad (3)$$

$\underline{\lambda}$ is constant, therefore

$$\underline{\lambda} = C_r \underline{r} (t_1) \quad (4)$$

and

$$\underline{p} (t_1) = C_v \underline{v} (t_1) = -(t_1 - t_0) \underline{\lambda} + \underline{p}_0 \quad (5)$$

Eqs. 1 to 5 are the basic equations which will now be applied to some special cases.

(A) Injection

Final position is not important, therefore

$$C_r = 0$$

$$\therefore \underline{\lambda} = 0$$

Therefore from (1)

$$\underline{a} = -\underline{p}_0$$

from (2)

$$\underline{v} (t_1) = (t_1 - t_0) \underline{f} - \underline{p}_0 (t_1 - t_0) + \underline{v}_0$$

$$\underline{v}_0 = \underline{v}_{p_0} - \underline{v}_T$$

$$\underline{v}(t_1) = (t_1 - t_0) \underline{f} - \underline{p}_0 (t_1 - t_0) + \underline{v}_p - \underline{v}_T$$

$$\underline{v}(t_1) + \underline{p}_0 (t_1 - t_0) = (t_1 - t_0) \underline{f} + \underline{v}_p - \underline{v}_T$$

from (5)

$$\underline{p}(t_1) = C_v \underline{v}(t_1) = - (t_1 - t_0) \underline{\lambda} + \underline{p}_0 = \underline{p}_0$$

since

$$\underline{\lambda} = 0$$

therefore \underline{p} is constant.

$$\underline{p}_0 = \frac{\underline{f}(t_1 - t_0) + \underline{v}_p - \underline{v}_T}{(t_1 - t_0) + \frac{1}{C_v}}$$

$$\underline{f} = \underline{f}_p - \underline{f}_T = \underline{g} - 0 = \text{constant}$$

Usually want

$$\underline{v}(t_1) = 0$$

then

$$C_v \rightarrow \infty$$

$$\underline{a}(t_1) = \underline{p}_0 = -\underline{g} - \frac{\underline{v}_p - \underline{v}_T}{t_1 - t_0}$$

sample data feedback law
where t_0 is latest sample time.

for continuous measurements

$$\underline{a} = -\underline{g} - \frac{\underline{v}_p - \underline{v}_T}{t_1 - t}$$

continuous feedback control law

(B) Interception

For interception, final velocity is not important, therefore

$$C_v = 0$$

$$\underline{a} = (t - t_0) \underline{\lambda} - \underline{p}_0$$

Therefore, one must determine $\underline{\lambda}$, \underline{p}_0

Assume $\underline{f} = 0$

$$\underline{\lambda} = C_r \left[\frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \underline{p}_0 \frac{(t_1 - t_0)^2}{2} + \underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]$$

$$\underline{p}_0 = (t_1 - t_0) \underline{\lambda}$$

$$\underline{\lambda} = C_r \left[\frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \frac{(t_1 - t_0)^3}{2} \underline{\lambda} + \underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]$$

$$\underline{\lambda} - C_r \frac{(t_1 - t_0)^3}{6} \underline{\lambda} + C_r \frac{(t_1 - t_0)^3}{2} \underline{\lambda} = C_r \left[\underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]$$

$$\frac{\underline{\lambda}}{C_r} - \frac{(t_1 - t_0)^3}{6} \underline{\lambda} + \frac{(t_1 - t_0)^3}{2} \underline{\lambda} = \underline{v}_0 (t_1 - t_0) + \underline{r}_0$$

Solving for $\underline{\lambda}$:

$$\underline{\lambda} = \frac{\underline{v}_0 (t_1 - t_0) + \underline{r}_0}{\frac{(t_1 - t_0)^3}{3} + \frac{1}{C_r}}$$

Solve for \underline{p}_0 in $\underline{p} = (t_1 - t_0) \underline{\lambda}$ to yield

$$p_0 = \frac{(t_1 - t_0) \left[\underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]}{\frac{(t_1 - t_0)^3}{3} + \frac{1}{C_r}}$$

$$\underline{a} = \frac{(t - t_0) \left[\underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]}{\frac{(t_1 - t_0)^3}{3} + \frac{1}{C_r}} - \frac{(t_1 - t_0) \left[\underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]}{\frac{(t_1 - t_0)^3}{3} + \frac{1}{C_r}}$$

Combining terms to yield

$$\underline{a} = - \frac{(t_1 - t) \left[\underline{v}_0 (t_1 - t_0) + \underline{r}_0 \right]}{\frac{(t_1 - t_0)^3}{3} + \frac{1}{C_r}} \quad \text{sample data case}$$

$$\underline{a} = - \frac{(t_1 - t) \left[\underline{v} (t_1 - t) + \underline{r} \right]}{\frac{(t_1 - t)^3}{3} + \frac{1}{C_r}} \quad \text{continuous feedback control law}$$

NOTE:

As $C_r \rightarrow \infty$, $\underline{r}(t_1) \rightarrow 0$ at the expense of large $\int_{t_0}^t a^2 dt$

$$\text{Or } \underline{a} \rightarrow \frac{-3 \left[\underline{v}(t_1 - t) + \underline{r} \right]}{(t_1 - t)^2} \quad \text{as } C_r \rightarrow \infty$$

(C) Rendezvous

To place pursuing body in immediate vicinity of target with small component of relative velocity.

$$\underline{a} = (t - t_0) \underline{\lambda} - \underline{p}_0$$

Assume $\underline{f} = 0$

This is reasonable if the distance from the target to pursuing body is small, since in this case

$$\underline{f}_p \approx \underline{f}_T$$

$$v(t_1) = 0 = \frac{(t_1 - t_0)^2}{2} \underline{\lambda} - \underline{p}_0 (t_1 - t_0) + \underline{v}_0$$

$$r(t_1) = 0 = \frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \underline{p}_0 \frac{(t_1 - t_0)^2}{2} + \underline{v}_0 (t_1 - t_0) + \underline{r}_0$$

$$\underline{p}_0 (t_1 - t_0) = \underline{v}_0 + \frac{(t_1 - t_0)^2}{2} \underline{\lambda}$$

$$\underline{p}_0 = \frac{\underline{v}_0}{t_1 - t_0} + \frac{t_1 - t_0}{2} \underline{\lambda}$$

$$0 = \frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \left[\frac{\underline{v}_0}{t_1 - t_0} + \frac{t_1 - t_0}{2} \underline{\lambda} \right] \frac{(t_1 - t_0)^2}{2} + \underline{v}_0 (t_1 - t_0) + \underline{r}_0$$

$$0 = \frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \underline{v}_0 \frac{(t_1 - t_0)}{2} - \frac{(t_1 - t_0)^3}{4} \underline{\lambda} + \underline{v}_0 (t_1 - t_0) + \underline{r}_0$$

$$-\frac{\underline{v}_0 (t_1 - t_0)}{2} - \underline{r}_0 = \frac{\underline{\lambda}}{12} \left[(t_1 - t_0)^3 \right]$$

$$\underline{\lambda} = \frac{-6 \underline{v}_0}{(t_1 - t_0)^2} - \frac{12 \underline{r}_0}{(t_1 - t_0)^3}$$

$$\underline{p}_0 = \frac{\underline{v}_0}{t_1 - t_0} + \frac{t_1 - t_0}{2} \left[-\frac{6 \underline{v}_0}{(t_1 - t_0)^2} - \frac{12 \underline{r}_0}{(t_1 - t_0)^3} \right]$$

$$\underline{p}_0 = \frac{\underline{v}_0}{t_1 - t_0} - \frac{3 \underline{v}_0}{t_1 - t_0} - \frac{6 \underline{r}_0}{(t_1 - t_0)^2}$$

$$\underline{p}_0 = -\frac{2 \underline{v}_0}{t_1 - t_0} - \frac{6 \underline{r}_0}{(t_1 - t_0)^2}$$

$$\underline{a} = (t - t_0) \left[\frac{-6 \underline{v}_0}{(t_1 - t_0)^2} - \frac{12 \underline{r}_0}{(t_1 - t_0)^3} \right] + \frac{2 \underline{v}_0}{t_1 - t_0} + \frac{6 \underline{r}_0}{(t_1 - t_0)^2}$$

$$\underline{a} = \frac{-6 \underline{v}_0}{t_1 - t_0} - \frac{12 \underline{r}_0}{(t_1 - t_0)^2} + \frac{2 \underline{v}_0}{t_1 - t_0} + \frac{6 \underline{r}_0}{(t_1 - t_0)^2}$$

$$\underline{a}(t) = \frac{-4 \underline{v}_0}{t_1 - t_0} - \frac{6 \underline{r}_0}{(t_1 - t_0)^2}$$

$$\underline{a}(t) = \frac{-4 v}{t_1 - t} - \frac{6 r}{(t_1 - t)^2}$$

(D) Soft Landing

Assume

$$\underline{f} = \underline{g} = \text{constant}$$

$$\underline{a} = (t - t_0) \underline{\lambda} - \underline{p}_0$$

$$0 = \frac{(t_1 - t_0)^2}{2} \underline{\lambda} - \underline{p}_0 (t_1 - t_0) + \underline{v}_0 + (t_1 - t_0) \underline{g}$$

$$0 = \frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \underline{p}_0 \frac{(t_1 - t_0)^2}{2} + \underline{v}_0 (t_1 - t_0) + \underline{r}_0 + \frac{(t_1 - t_0)^2}{2} \underline{g}$$

$$\underline{p}_0 = \frac{\underline{v}_0}{t_1 - t_0} + \frac{t_1 - t_0}{2} \underline{\lambda} + \underline{g}$$

$$0 = \frac{(t_1 - t_0)^3}{6} \underline{\lambda} - \frac{1}{2} \left[\frac{\underline{v}_0}{t_1 - t_0} + \frac{t_1 - t_0}{2} \underline{\lambda} + \underline{g} \right] (t_1 - t_0)^2 + \underline{v}_0 (t_1 - t_0)$$

Solve for \underline{p}_0 , $\underline{\lambda}$ and substitute in equation for \underline{a} to yield

$$\underline{a} = \frac{-4 \underline{v}}{t_1 - t} - \frac{6 \underline{r}}{(t_1 - t)^2} - \underline{g}$$